

Clock Radio

- **Repeat Alarm**

Switches off the alarm for 9 minutes.

- **Wake Up to Radio or Buzzer**

Gives you the choice of waking up to your favourite radio station or alarm buzzer.

- **Alarm Reset**

Automatically resets the alarm for the same time on the next day, so you don't have to keep manually resetting the alarm.

- **Easy Alarm/Time Set**

- **Slumber**

- **Battery Back-Up**

* AJ3195 is a quartz-operated version which ensures the time stays correct whilst mains frequencies may fluctuate



Standard product information

Clock/Alarm

- Electronic clock
- Quartz-operated clock : AJ3195 /01, /14, /12*
- Wake up by radio or buzzer
- Alarm : Single alarm (radio & buzzer),
Slumber function, Repeat alarm (9 minutes)
- Time/alarm setting : Hours/minutes

Tuner

- FM/AM tuning
- Wavebands : /04 : FM stereo/LW
/00, /01, /05, /13, /19 : FM stereo/MW
/14 : FM Stereo (Ext)/MW
/11, /12* : FM stereo/MW
/10 : FM/AM
- Frequency ranges : FM 87.5 - 108 MHz
/14 : FM 65 - 108 MHz
MW 525 - 1607 kHz
LW 148.5 - 284 kHz
AM 530 - 1710 kHz

Amplifier

- Max. output power (RMS)
(± 1 dB ; D < 10%) : 80 m Watts

Sound System

- Loudspeaker : 64 mm (2.5")

Display

- Red LED : 0.6" (15 mm) digit height
- Clock indication : 24 hours
/01, /10, /13, /11, /12*, /19 : 12 hours with pm indication

Power Supply

- AC mains : /01, /11, /19 : 120/230 V, 50/60 Hz (switchable)
/00, /04, /05, /14 : 230 V, 50 Hz
/12* : 230 V, 50 Hz
/13 : 220 V, 60 Hz
- Backup battery : 6F22, 9 V (not included)

General

- Material : Polystyrene
- Weight : 0.6 Kg
- Dimensions : 192 mm W x 52 mm H x 152 mm D
- Packaging dimensions : 235 mm W x 75 mm H x 176 mm D
- Packaging dimensions : 270 mm W x 75 mm H x 176 mm D
(for /05, /10)
- Quantity /mastercarton : 4

* /12 is SKD of /01 for India

Product Highlights

• FM/MW or FM/LW Tuner

Gives you a wide selection of radio stations to choose from.

• LED

Fashionable, red backlit display.

• Slumber

Lets you enjoy up to 59 minutes of radio entertainment while going to sleep.

After the pre-set time the radio switches off automatically.

• Battery Back-Up

A 9-Volt battery (not included) ensures that clock and alarm settings are maintained in the event of a mains interrupt or failure. Should this happen the display will not illuminate but the alarm and clock settings remain active.

• Radio On/Off Switch